

TECHNICAL DATA

# Fluke 9062 Motor and Phase Rotation Indicator



## Key features

- 3 phase indication
- Indication of phase rotation
- Indication of motor rotation direction
- Contact free determination of the rotation direction of running motors

## Product overview: Fluke 9062 Motor and Phase Rotation Indicator

Unique phase rotation indicator with motor rotation ability

The unique Fluke 9062 provides rotary field and motor rotation indication with the benefits of contact-less detection. Purpose made for commercial and industrial environments, the Fluke 9062 provides rapid indication of 3 phase rotation using test leads supplied or can be used to determine motor rotation on synchronous and asynchronous 3 phase motors. The contact-less detection is ideal for use on motors where the shaft is not visible. The included test probes have a variable clamping range for safe contact, also in industrial sockets.

## Specifications: Fluke 9062 Motor and Phase Rotation Indicator

Technical specifications

Voltage range

Up to 400 V

Phase display	120-400 V AC
Frequency range	2-400 Hz
Operating timer	Continuous
<b>Environmental specifications</b>	
Operating temperature	0 °C to 40 °C
Operating altitude	Up to 2000m
Humidity (without condensation)	15% to 80%
Dust/water resistance	IP 40
<b>Safety specifications</b>	
Electrical safety	EN 61010,
	EN 61557-7
Overvoltage category	CAT III, 300 V
<b>Mechanical and general specifications</b>	
Size	124 x 61 x 27 mm
Weight	1 x 9 V
Batteries	1 x 9 V
Warranty	2 years

## Ordering information



### **Fluke 9062 Motor and Phase Rotation Indicator**

Fluke 9062 Motor and Phase Rotation Indicator

- Test leads (3)
- Test probes (3)
- Alligator clips (3)
- Battery, 9 V
- User manual

Fluke. *Keeping your world up and running.*®

**Fluke (UK) Ltd.**  
52 Hurricane Way  
Norwich, Norfolk  
NR6 6JB  
United Kingdom  
Tel.: +44 (0)20 7942 0708  
E-mail: [cs.uk@fluke.com](mailto:cs.uk@fluke.com)  
[www.fluke.com/en-gb](http://www.fluke.com/en-gb)

©2024 Fluke Corporation. All rights reserved.  
Data subject to alteration without notice.  
09/2024

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**